

**JOB NAME** \_\_\_\_\_

**Type** \_\_\_\_\_

**CATALOG NUMBER** \_\_\_\_\_

**CH 180 Series**



14" dia W x 36"H (356 x 914mm)

**CH 180-6** illustrated  
with options:  
Metal Channel Accents **-MCA**  
Hanging Yoke **-HK**  
Chain Suspension **-CHN**  
Finish Color **-ABZ**



14" dia W x 60"H (356 x 1524mm)

**CH 182-4** illustrated  
with options:  
Downlight **-DL**  
Decorative Banding **-DB**  
Extended Top **-ET**  
Stem Suspension **-STM**  
Finish Color **-ABZ**

**Specifications**

**Construction**

- Diffuser is .125" white acrylic and canopy is 20 gauge steel
- Flat diffuser provided in bottom unless other options are selected
- Finish is textured powder coat polyester
- 3/4" x 1" wood accents are stained golden oak unless otherwise specified
- 7/8 O.D. stem or 7/32" chain is provided in length as required for specified overall suspended height

**Electrical**

- Integral multiple-lamp electronic ballasts are wired to allow 40 watt long compact or 32 watt T8 fluorescent lamps on opposite sides of interior channel to be powered by each ballast
- Lamps may be split into two circuits for remotely switched two-level illumination
- 120V-277V electronic ballasts are standard
- Optional single incandescent reflector lamp downlight has concentric louver assembly below for glare control
- Mounting plate above canopy mounts to ceiling structure and covers junction box
- Loop on stem meets seismic requirements

**Catalog Number**

Lamps	4 lamps	6 lamps	8 lamps	9 lamps
40W compact fluorescent (FT40W/2G11/RS)	<input type="checkbox"/> <b>CH 180-4</b>	<input type="checkbox"/> <b>CH 180-6</b>	<input type="checkbox"/> <b>CH 180-8</b>	
32W T8 fluorescent (F32T8)	<input type="checkbox"/> <b>CH 182-4</b>	<input type="checkbox"/> <b>CH 182-6</b>	<input type="checkbox"/> <b>CH 182-8</b>	
Six 100W A19 maximum incandescent		<input type="checkbox"/> <b>CH 180-INC</b>		
Nine 100W A19 maximum incandescent				<input type="checkbox"/> <b>CH 182-INC</b>
<i>Example: CH 180-4-MCA-HK-CHN-ABZ-55"</i>				

**Options**

**Suspension:**

Black chain: Add suffix  **-CHN**.

Black stem: Add suffix  **-STM**.

**Finish Color:**

Antique bronze vein: Add suffix  **-ABZ**.

Antique Copper Vein: Add suffix  **-ACP**.

**Downlight:** Single medium base socket at bottom for 300 watt (max.) incandescent reflector lamp.

Includes concentric louver in lieu of bottom diffuser. Add suffix  **-DL**.

**Hanging Yoke:** Provides alternate connection from chain to fixture body. Not with -ET.

Add suffix  **-HK**.

**Extended Top:** Provides stepped top structure for alternate appearance. Not with -HK.

Add suffix  **-ET**.

**Delete Wood Accents:** Add suffix  **-DWA**.

**Metal Channel Accents:** Provides steel side channels in lieu of wood. Add suffix  **-MCA**.

**Dimming Ballasts:** For use with Advance Mark X two-wire control system for 5%-100% range.

Add suffix  **-DIM**.